

In-line "A-weighting" Filter

For Acoustic Measurements Utilizing "Prepolarized" Microphones
and ICP® Microphone Preamplifiers

- Meets ANSI S1.4 (R2001) and IEC60651 (2001-10) Type 1 Sound Level Meter Standards for A-weighting filter
- Installs Between ICP® Microphone Preamplifier and ICP® Sensor Signal Conditioner
- Connects with Low-cost Coaxial Cable
- Supports Use of TEDS-capable ICP® Microphone Preamplifiers
- Provides Cost-effective "A-weighting" Solution

Model 426B02 In-line Filter is used in conjunction with an ICP® preamplifier to provide A-weighting for acoustic measurements. The filter can be used with PCB® microphone preamplifier Models 426B03 and 426D01. The filter and preamplifier are powered by low-cost, constant current (4-20 mA) excitation commonly used with ICP® sensors. The in-line filter is inserted between the preamplifier and the constant current source. Since the system is low impedance, low-cost cables can be used, greatly reducing overall signal conditioning costs.

Designed for stability over a wide range of environmental conditions, the filter's frequency response is weighted according to the A-weighting filter portion of both ANSI S1.4 and IEC 60651 Type 1 Sound Level Meter Standards; however, the tolerances are tighter than the Type 1 tolerance in these standards. The tighter tolerances permit the filter to be added to the system without compromising the Type 1 standards for the system. The filter supports "Smart Transducer Interface" IEEE P1451.4 with TEDS (Transducer Electronic Data Sheet) by passing TEDS data from the preamplifier through the filter.

As with all PCB® instrumentation, this equipment is complemented with toll-free applications assistance, 24-hour customer service, and is backed by a no-risk policy that guarantees satisfaction or your money refunded.



Model 426B02
In-line "A-weighting" Filter



MODEL 426B02 IN-LINE "A-WEIGHTING" FILTER

Specifications

Model 426B02		
Performance	English	SI
Frequency Response (A-weighted) (± 0.5 dB) ^[1] (± 1.0 dB) ^[1]	50 to 8000 Hz 20 to 20,000 Hz	
Gain (at 1 kHz)	0.0 \pm 0.3 dB	
Output Voltage (Max) (< -50 dB THD, 1 kHz)	3.5 V pk	
Output (Max) (with 50 mV/Pa microphone) (with 12.5 mV/Pa microphone)	131 dB 143 dB	
Environmental		
Temperature Sensitivity (-40 to +149 °F (-40 to +65 °C))	± 0.5 dB	
Maximum Temperature (Operating)	176 °F	80 °C
Humidity Sensitivity (0 to 95% RH, non-condensing) ^[2]	± 0.5 dB	
Electrical		
Electrical Noise (Flat, 20 to 20k Hz) (1/3 octave band @ 1k Hz)	< 25.0 μ V < 2.8 μ V	
Input Impedance	30 kohm	
Output Impedance	50 ohm	
Excitation Voltage	24 to 32 VDC	
Constant Current Excitation	4-20 mA	
Current Output (delivered to preamplifier) (± 0.15 mA) ^[3]	0.75 mA	
Cable Driving Capability (100 ft (30.4 m) cable length) ^{[3][4]}	3.5 V pk, to 30.3 kHz	
Physical		
Electrical Connector (input) (output)	BNC Plug BNC Jack	
Size (diameter x length)	0.57 x 3.66 in	14.5 x 93 mm

Notes: [1] re 1 kHz [2] at +104 °F (+40 °C) [3] for best performance, filter should be installed next to the preamplifier [4] with 4 mA excitation and 300 pF total cable capacitance

Related Equipment



Model 482C
1, 4, or 8-channel, multi-purpose ICP® sensor signal conditioner with AC, DC or battery power



Model 480M122
Single-channel, battery powered ICP® sensor signal conditioner with 4 mA, 28 VDC excitation



Model 426D01
ICP® preamplifier for 1/2-inch Prepolarized Microphones



Model 426B03
ICP® preamplifier for 1/4-inch Prepolarized Microphones



Model 377A02
1/2-inch prepolarized Free-field Microphone



Model 377A11
1/2-inch prepolarized Pressure Microphone



Model 377A20
1/2-inch prepolarized Random Incidence Microphone



Model 377A10
1/4-inch prepolarized Pressure Microphone



Model 377A01
1/4-inch prepolarized Free-field Microphone



Series 003B
Coaxial Cable
10-32 Plug to BNC Jack



Series 003D
Coaxial Cable
BNC Plug to BNC Plug



3425 Walden Avenue, Depew, NY 14043-2495 USA

Toll free 888-684-0013

24-hour SensorLineSM 716-684-0001

Fax 716-685-3886 E-mail acoustics@pcb.com

Web site www.pcb.com

AS9100:2004 CERTIFIED ISO 9001:2000 CERTIFIED A2LA ACCREDITED to ISO 17025

© 2007 PCB Group, Inc. In the interest of constant product improvement, specifications are subject to change without notice. PCB, ICP, and Modally Tuned are registered trademarks of PCB Group, Inc.

SensorLine is a service mark of PCB Group, Inc. All other trademarks are properties of their respective owners.

VIB-426B02-1207

Printed in U.S.A.

PCB® Piezotronics, Inc. specializes in the development, application, and support of shock and vibration sensors, microphones, impact hammers, piezoelectric actuators, and dynamic strain sensors for acceleration measurements, acoustic testing, and structural testing requirements. This product focus, coupled with the strengths and resources of PCB, permits us to offer exceptional customer service, 24-hour technical assistance, and a **Total Customer Satisfaction** guarantee.

Visit www.pcb.com to locate your nearest sales office