

	ENGLISH	SI	
Performance			
Sensitivity(± 0.5 %)(Voltage)	100 mV/g	10.2 mV/(m/s ²)	[1]
Measurement Range(± 5V)(Output)	50 ±g pk	490 ±m/s ² pk	
Frequency Range(± 2 %)	5 to 5,000 Hz	5 to 5,000 Hz	
Frequency Range(± 5 %)	0.5 to 10,000 Hz	0.5 to 10,000 Hz	
Frequency Range(± 10 %)	0.3 to 14,000 Hz	0.3 to 14,000 Hz	
Resonant Frequency(Mounted)	≥ 35 kHz	≥ 35 kHz	
Broadband Resolution(1 Hz to 10 kHz)	0.004 g rms	0.039 m/s ² rms	[2]
Amplitude Linearity	≤ 1 %	≤ 1 %	[3]
Transverse Sensitivity	≤ 3 %	≤ 3 %	
Sensitivity(Base Strain)	0.0001 g/µε	0.001 (m/s ²)/µε	
Environmental			
Warm Up	< 12.0 sec	< 12.0 sec	
Temperature Range(Operating)	-65 to +250 °F	-54 to +121 °C	
Electrical			
Spectral Noise(1 Hz)	235 (µm/s ²)/√Hz	2,303	[2]
Spectral Noise(10 Hz)	55 (µm/s ²)/√Hz	539	[2]
Spectral Noise(100 Hz)	18 (µm/s ²)/√Hz	176	[2]
Spectral Noise(1 kHz)	12 (µm/s ²)/√Hz	118	[2]
Physical			
Sensing Element	Quartz/Shear	Quartz/Shear	
Housing Material	Stainless Steel/Welded	Stainless Steel/Welded	
Size (Hex x Height x Height x Width x Depth)	1.19 in x 1.5 in x 6.3 in x 2.4 in x 30.2 mm x 38.1 mm x 16 cm x		
	11.0 in	6.1 cm x 28 cm	
Weight	6.2 oz	176 gm	[2]
Electrical Connector	10-32 Coaxial/Side	10-32 Coaxial/Side	
Mounting Thread(Standard)	1/4-28 UNF	1/4-28 UNF	
Mounting Thread(Unit Under Test)	10-32 UNF	10-32 UNF	
Mounting Torque	20 to 30 in-lb	225 to 338 N-cm	
Power(± 5%)(Required)	36 VDC	36 VDC	[4]
Weight	1.51 lb	685 gm	[2]
Cable Connector(Input)	BNC Jack/Rear	BNC Jack/Rear	
Cable Connector(Output)	BNC Jack/Rear	BNC Jack/Rear	

OPTIONAL VERSIONS		
Optional versions have identical specifications and accessories as listed for the standard model except where noted below. More than one option may be used. [5]		
M - Metric Mount Sensitivity± 0.5	10 mV/(m/s ²)	98 mV/g

NOTES:

[1]All sensor specifications are valid only when used with matched power supply.
 [2]Typical.
 [3]Zero-based, least-squares, straight line method.
 [4]Provided by 488A04.
 [5]Measured at 159 Hz.

SUPPLIED ACCESSORIES:

Model 003C10 Low-noise, blue, coaxial, PTFE cable, 10-ft, 10-32 coaxial plug to BNC plug (1)
 Model 003D03 Low-noise, blue, coaxial, PTFE cable, 3-ft, BNC plug to BNC plug (1)
 Model 017AXX Power Cord (1)
 Model 080A149 Calibration adaptor, 10-32 to 5-40 (for Model 394A11 calibration standard) (1)
 Model 081A08 Mounting Stud (10-32 to 1/4-28) (2)
 Model 081A90 Mounting stud, 10-32 to 5-40 (2)
 Model 081B05 Mounting Stud (10-32 to 10-32) (2)
 Model 081B20 Mounting Stud, with shoulder (1/4-28 to 1/4-28) (2)
 Model 301A11 Calibration ICP® accel., 100 mV/g, 50g, 0.5 to 10 kHz, 10-32 side conn., 1/4-28 thd on bottom, 10-32 thd on top (1)
 Model 482A23 1-channel, line-powered, ICP® sensor signal cond., BNC input/output conn. X0.9 to x1.1 gain, (for use in 394A10/394A11 systems) (1)
 Model 488B04 Power Supply, 100 to 125 VAC or 200 to 250 VAC input, 27 VDC @ 20 mA output. (1)
 Model ACS-1 NIST traceable frequency response (10 Hz to upper 5% point).
 Model ACS-10/ACS-4 NIST Tracable frequency sweep (0.5 Hz to upper 5% point) (1)
 Model ACS-4 Single axis, low frequency phase and amplitude response cal (from 0.5 to 10Hz)
 Model M080A149 Mounting adaptor (10-32 to M3 x 0.50) (1)
 Model M081B05 Mounting Stud 10-32 to M6 X 0.75 (2)
 Model M081B20 Mounting Stud 1/4-28 to M6 X 0.75 (2)

Entered: LK	Engineer: CPH	Sales: WDC	Approved: DY	Spec Number:
Date: 10/18/2019	Date: 10/18/2019	Date: 10/18/2019	Date: 10/18/2019	11307

Phone: 716-684-0001
Fax: 716-684-0987
E-Mail: info@pcb.com

3425 Walden Avenue, Depew, NY 14043

All specifications are at room temperature unless otherwise specified.
 In the interest of constant product improvement, we reserve the right to change specifications without notice.